


PTFB090901EA/FA

Thermally-Enhanced High Power RF LDMOS FETs 90 W, 28 V, 920 – 960 MHz


Description

The PTFB090901EA and PTFB090901FA are 90-watt LDMOS FETs intended for use in multi-standard cellular power amplifier applications in the 920 to 960 MHz frequency band. Features include input and output matching, high gain and thermally-enhanced packages. Manufactured with Wolfspeed's advanced LDMOS process, these devices provide excellent thermal performance and superior reliability.

PTFB090901EA
Package H-36265-2



PTFB090901FA
Package H-37265-2



Features

- Input and output internal matching
- Typical CW performance, 960 MHz, 28 V
 - Output power at $P_{1dB} = 90\text{ W}$
 - Efficiency = 65%
- Typical two-carrier WCDMA performance, 960 MHz, 28 V
 - Average output power = 20 W
 - Linear Gain = 20.8 dB
 - Efficiency = 35%
 - Intermodulation distortion = -35 dBc
- Integrated ESD protection
- Low thermal resistance
- Pb-free and RoHS-compliant
- Capable of handling 10:1 VSWR @ 28 V, 90 W (CW) output power

RF Characteristics

Single-carrier WCDMA Specifications (tested in Wolfspeed test fixture)

$V_{DD} = 28\text{ V}$, $I_{DQ} = 650\text{ mA}$, $P_{OUT} = 25\text{ W}$ average, $f = 960\text{ MHz}$
 3GPP signal, PAR = 10 dB @ 0.01% CCDF probability, channel bandwidth = 3.84 MHz

Characteristic	Symbol	Min	Typ	Max	Unit
Gain	G_{ps}	19	19.5	—	dB
Drain Efficiency	η_D	36	40	—	%
Adjacent Channel Power Ratio	ACPR	—	-35	-31.5	dBc

All published data at $T_{CASE} = 25^\circ\text{C}$ unless otherwise indicated

ESD: Electrostatic discharge sensitive device—observe handling precautions!

RF Characteristics (cont.)

Two-tone Specifications (not subject to production test—verified by design/characterization in Wolfspeed test fixture)
 $V_{DD} = 28\text{ V}$, $I_{DQ} = 650\text{ mA}$, $P_{OUT} = 70\text{ W PEP}$, $f = 960\text{ MHz}$, tone spacing = 1 MHz

Characteristic	Symbol	Min	Typ	Max	Unit
Gain	G_{ps}	—	19.5	—	dB
Drain Efficiency	η_D	—	48	—	%
Intermodulation Distortion	IMD	—	-30	—	dBc

DC Characteristics

Characteristic	Conditions	Symbol	Min	Typ	Max	Unit
Drain-source Breakdown Voltage	$V_{GS} = 0\text{ V}$, $I_{DS} = 10\text{ mA}$	$V_{(BR)DSS}$	65	—	—	V
Drain Leakage Current	$V_{DS} = 28\text{ V}$, $V_{GS} = 0\text{ V}$	I_{DSS}	—	—	1.0	μA
	$V_{DS} = 63\text{ V}$, $V_{GS} = 0\text{ V}$	I_{DSS}	—	—	10.0	μA
On-state Resistance	$V_{GS} = 10\text{ V}$, $V_{DS} = 0.1\text{ V}$	$R_{DS(on)}$	—	0.123	—	Ω
Operating Gate Voltage	$V_{DS} = 28\text{ V}$, $I_{DQ} = 650\text{ mA}$	V_{GS}	—	3.8	—	V
Gate Leakage Current	$V_{GS} = 10\text{ V}$, $V_{DS} = 0\text{ V}$	I_{GSS}	—	—	1.0	μA





Maximum Ratings

Parameter	Symbol	Value	Unit
Drain-source Voltage	V_{DSS}	65	V
Gate-source Voltage	V_{GS}	-6 to +10	V
Junction Temperature	T_J	200	$^{\circ}\text{C}$
Storage Temperature Range	T_{STG}	-40 to +150	$^{\circ}\text{C}$
Thermal Resistance ($T_{CASE} = 70^{\circ}\text{C}$, 85 W CW)	$R_{\theta JC}$	0.73	$^{\circ}\text{C/W}$

Ordering Information





Type and Version	Order Code	Package	Package Description	Shipping
PTFB090901EA V2 R0	PTFB090901EA-V2-R0	H-36265-2	Ceramic open-cavity, bolt-down	Tape & Reel, 50 pcs
PTFB090901EA V2 R250	PTFB090901EA-V2-R250	H-36265-2	Ceramic open-cavity, bolt-down	Tape & Reel, 250 pcs
PTFB090901FA V2 R0	PTFB090901FA-V2-R0	H-37265-2	Ceramic open-cavity, earless	Tape & Reel, 50 pcs
PTFB090901FA V2 R250	PTFB090901FA-V2-R250	H-37265-2	Ceramic open-cavity, earless	Tape & Reel, 250 pcs

Typical Performance (data taken in a production test fixture)









Typical Performance (cont.)




Typical Performance (cont.)




Broadband Circuit Impedance

Frequency MHz	Z Source Ω		Z Load Ω	
	R	jX	R	jX
900	2.3	-6.4	3.8	-2.6
920	2.2	-6.2	3.6	-2.3
940	2.1	-6.0	3.5	-2.1
960	1.9	-5.8	3.4	-1.8
980	1.8	-5.6	3.3	-1.6


See next page for reference circuit information



Reference Circuit



Reference circuit input schematic for $f = 960 \text{ MHz}$



Reference circuit output schematic for $f = 960 \text{ MHz}$

Reference Circuit (cont.)**Reference Circuit Assembly**

DUT PTFB090901EA or PTFB090901FA

Reference Circuit Part No. LTN/PTFB090901EA (PTFB090901EA) LTN/PTFB090901FA (PTFB090901FA)

PCB Rogers RO4350, 0.508 mm [0.020"] thick, 2 oz. copper, $\epsilon_r = 3.48$ Find Gerber files for this test fixture on the Wolfspeed Web site at www.wolfspeed.com/RF**Electrical Characteristics at 960 MHz**


Transmission Line	Electrical Characteristics	Dimensions: mm	Dimensions: mils
Input			
TL102	0.0064 λ , 69.6 Ω	W = 0.65, L = 1.23	W = 25, L = 48
TL103	0.1238 λ , 51.53 Ω	W = 1.1, L = 23.38	W = 43, L = 921
TL104	0.1658 λ , 69.6 Ω	W = 0.65, L = 31.91	W = 25, L = 1256
TL105	0.0205 λ , 69.6 Ω	W = 0.65, L = 3.94	W = 25, L = 155
TL106	0.0014 λ , 26.81 Ω	W = 2.79, L = 0.25	W = 110, L = 10
TL107	0.0195 λ , 7.47 Ω	W = 12.37, L = 3.37	W = 487, L = 133
TL108	0.0014 λ , 26.81 Ω	W = 2.79, L = 0.25	W = 110, L = 10
TL109	0.0369 λ , 51.53 Ω	W = 1.1, L = 6.97	W = 43, L = 275
TL114, TL115, TL116, TL117, TL118, TL119	0.014 λ , 26.81 Ω	W1 = 2.79, W2 = 2.79, W3 = 2.54	W1 = 110, W2 = 110, W3 = 100
TL120	0.0037 λ , 7.47 Ω	W1 = 12.37, W2 = 12.37, W3 = 0.65	W1 = 487, W2 = 487, W3 = 25
TL122	0.0294 λ , 7.47 Ω	W = 12.37, L = 5.08	W = 487, L = 200
TL123	0.0094 λ , 51.53 Ω	W1 = 1.1, W2 = 1.1, W3 = 1.78	W1 = 43, W2 = 43, W3 = 70
TL124	0.0183 λ , 51.53 Ω	W = 1.1, L = 3.45	W = 43, L = 136
TL126, TL128	0.0055 λ , 34.08 Ω	W = 2.03, L = 1.02	W = 80, L = 40

Reference Circuit (cont.)

Electrical Characteristics at 960 MHz (cont.)

Transmission Line	Electrical Characteristics	Dimensions: mm	Dimensions: mils
Output			
TL201	0.055 λ , 9.74 Ω	W = 9.25, L = 9.65	W = 364, L = 380
TL202	0.010 λ , 11.08 Ω	W1 = 8, W2 = 8, W3 = 1.78	W1 = 315, W2 = 315, W3 = 70
TL203	0.081 λ , 11.08 Ω	W = 8, L = 14.2	W = 315, L = 559
TL204, TL243	0.008 λ , 47.12 Ω	W1 = 1.27, W2 = 1.27, W3 = 1.52	W1 = 50, W2 = 50, W3 = 60
TL205, TL214	0.011 λ , 47.12 Ω	W1 = 1.27, W2 = 1.27, W3 = 2.03	W1 = 50, W2 = 50, W3 = 80
TL206, TL213, TL217, TL219	0.009 λ , 9.74 Ω	W1 = 9.25, W2 = 9.25, W3 = 1.52	W1 = 364, W2 = 364, W3 = 60
TL207	0.007 λ , 47.12 Ω	W = 1.27, L = 1.4	W = 50, L = 55
TL209	0.030 λ , 9.74 Ω	W = 9.25, L = 5.21	W = 364, L = 205
TL210	0.075 λ , 47.12 Ω	W = 1.27, L = 14.05	W = 50, L = 553
TL211, TL232	0.002 λ , 47.12 Ω	W = 1.27, L = 0.38	W = 50, L = 15
TL212	0.060 λ , 47.12 Ω	W = 1.27, L = 11.2	W = 50, L = 441
TL215	0.055 λ , 9.74 Ω	W = 9.25, L = 9.65	W = 364, L = 380
TL216	0.007 λ , 47.12 Ω	W = 1.27, L = 1.4	W = 50, L = 55
TL218	0.007 λ , 47.12 Ω	W1 = 1.27, W2 = 1.27, W3 = 1.27	W1 = 50, W2 = 50, W3 = 50
TL221	0.006 λ , 38.69 Ω	W = 1.7, L = 1.14	W = 67, L = 45
TL222, TL223	0.061 λ , 38.69 Ω	W = 1.7, L = 11.3	W = 67, L = 445
TL224	0.030 λ , 51.46 Ω	W = 1.1, L = 5.69	W = 43, L = 224
TL225	0.012 λ , 38.69 Ω	W = 1.7, L = 2.22	W = 67, L = 87
TL226	0.073 λ , 11.08 Ω	W = 8, L = 12.7	W = 315, L = 500
TL231	0.060 λ , 47.12 Ω	W = 1.27, L = 11.2	W = 50, L = 441
TL233	0.075 λ , 47.12 Ω	W = 1.27, L = 14.05	W = 50, L = 553
TL234	0.030 λ , 9.74 Ω	W = 9.25, L = 5.21	W = 364, L = 205
TL235, TL236	0.014 λ , 9.74 Ω	W1 = 9.25, W2 = 9.25, W3 = 2.36	W1 = 364, W2 = 364, W3 = 93
TL237, TL239	0.082 λ , 47.12 Ω	W = 1.27, L = 15.35	W = 50, L = 604
TL240, TL241	0.009 λ , 47.12 Ω	W1 = 1.27, W2 = 1.27, W3 = 1.78	W1 = 50, W2 = 50, W3 = 70
TL242	0.007 λ , 47.12 Ω	W1 = 1.27, W2 = 1.27, W3 = 1.27	W1 = 50, W2 = 50, W3 = 50
TL245	0.017 λ , 11.08 Ω	W = 8, L = 2.92	W = 315, L = 115

Reference Circuit (cont.)



Reference circuit assembly diagram (not to scale)

Component ID	Description	Manufacturer	P/N
Input			
C101	Chip capacitor, 33 pF	ATC	100B330FW500XB
C102	Chip capacitor, 10000 pF	ATC	200B103MW
C103	Chip capacitor, 4.7 pF	ATC	100B4R7BW500XB
C104	Chip capacitor, 4.7 μF	Nichicon	F931C475MAA
C105	Chip capacitor, 10000 pF	ATC	200B103MW
C106, C107	Chip capacitor, 4.8 pF	ATC	100B4R8BW500XB
C108	Chip capacitor, 1.5 pF	ATC	100B1R5BW500XB
C109	Chip capacitor, 8.2 pF	ATC	100B8R2BW500XB
C801, C804	Chip capacitor, 0.1 μF	Panasonic Electronic Components	ECJ-3VB1H104K
C802, C803, C805	Chip capacitor, 1,000 pF	Panasonic Electronic Components	ECJ-1VB1H102K
R801	Resistor, 1.0k Ω	Panasonic Electronic Components	ERJ-8GEYJ102V
R802	Resistor, 1.3k Ω	Panasonic Electronic Components	ERJ-8GEYJ132V
R803	Resistor, 1.2k Ω	Panasonic Electronic Components	ERJ-8GEYJ122V
R804, R805	Resistor, 10 Ω	Panasonic Electronic Components	ERJ-8GEYJ100V


table cont. next page

Reference Circuit (cont.)


Component ID	Description	Manufacturer	P/N
Input (cont.)			
S1	Transistor	Fairchild Semiconductor	BCP56
S2	Potentiometer, 2k Ω	Bourns Inc.	3224W-1-202E
S3	Voltage Regulator	National Semiconductor	LM7805
Output			
C201	Chip capacitor, 1 pF	ATC	100B0R9BW500XB
C202, C207, C215, C216	Chip capacitor, 1.0 μ F	ATC	281M5002106K
C203, C213	Chip capacitor, 0.1 μ F	Panasonic Electronic Components	ECJ-3VB1H104K
C204, C212	Chip capacitor, 1 μ F	AVX Corporation	2225PC105KAT1A
C205, C209	Capacitor, 10 μ F	Taiyo Yuden	UMK325C7106MM-T
C206, C208	Chip capacitor, 33 pF	ATC	100B330JW500XB
C210, C211	Chip capacitor, 3 pF	ATC	100B2R5BW500XB
C214	Chip capacitor, 33 pF	ATC	100B330FW500XB

See next page for package outline

Package Outline Specifications



Package Outline Specifications (cont.)



Revision History

Revision	Date	Data Sheet Type	Page	Subjects (major changes at each revision)
01	2010-09-02	Advance	All	New product PTFB090801FA, proposed only.
02	2010-11-05	Advance	All	Product number revised.
03	2011-09-08	Advance	All	Added eared package H-36265-2
04	2012-02-23	Production	All	Products released to production: specifications finalized, circuit information added.
05	2013-01-23	Production	All	Version 2 (V2) products will replace previous Version 1 (V1) products. No change to form, fit or function.
05.1	2014-07-08	Production	7 10-11	Correct label for output schematic. Identify component manufacturer and part number.
05.2	2016-06-09	Production	2	Updated ordering code to R0
06	2018-06-22	Production	All	Converted to Wolfspeed Data Sheet

For more information, please contact:

4600 Silicon Drive
Durham, North Carolina, USA 27703
www.wolfspeed.com/RF

Sales Contact
RFSales@wolfspeed.com

RF Product Marketing Contact
RFMarketing@wolfspeed.com
919.407.7816

Notes

Disclaimer

Specifications are subject to change without notice. Cree, Inc. believes the information contained within this data sheet to be accurate and reliable. However, no responsibility is assumed by Cree for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Cree. Cree makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose. "Typical" parameters are the average values expected by Cree in large quantities and are provided for information purposes only. These values can and do vary in different applications and actual performance can vary over time. All operating parameters should be validated by customer's technical experts for each application. Cree products are not designed, intended or authorized for use as components in applications intended for surgical implant into the body or to support or sustain life, in applications in which the failure of the Cree product could result in personal injury or death or in applications for planning, construction, maintenance or direct operation of a nuclear facility.